




[HOME](#) [ABOUT US](#) [SERVICES](#) [PRODUCTS](#) [CONTACT US](#) [SITE TOOLS](#) [GUESTBOOK](#)
[CPU Coolers](#) > Cofan Part #: P4B47801


Intel Pentium IV Socket 478  
for 1.3 GHz to 3.0 GHz

[Features](#) [Thermal Characteristics](#) [Heat Sink](#) [Integrated Fan](#) [PDF Document](#) [Miscellaneous](#)

#### Features

- Cross cut heat sink provides improved heat dissipation.
- Pre-applied Chomerics T-725 Thermal Interface.
- Easy to install clip.

Note: Thermal test done at 78 Watts in open air.

#### Thermal Characteristics

Thermal Resistance, Plate to Ambient: 0.268 °C/W

#### Heat Sink

Alloy	Extrusion 6063 T5 Aluminum
Pedestal Size (L x W)	1.96" x 2.13" ( 49.78mm x 54.10 mm )
Pedestal Flatness	3/1000 per linear inch
Mechanical Mounting	2 Piece Lever Type Clips

#### Integrated Fan

Cofan Model:	F-610HH12CII
Size (LxWxH):	60.0 mm x 60.0 mm x 10.0 mm
Air Flow:	21.01 CFM at 4800 RPM
Air Pressure:	0.179 InH <sub>2</sub> O (4.54 mmH <sub>2</sub> O)
Acoustic Noise	36.1 dBA
Input Power:	12 VDC, max. 0.27 Amp
Connector:	3 pin position, Molex 22-01-3037
Tachometer Sensor Output:	Open Collector, TTL Signal, 2 Pulses per revolution
MTBF:	70,000 hrs at 25°C

#### PDF Document

[Download Specification](#)

[Terms of Use](#)

[Miscellaneous](#)

Copyright © 1994-2008 Cofan USA, Inc. All Rights Reserved. 